

Dual Power supply for up to two ARI's Preamplifiers.

## Model: P-15D



The P-15D is a low noise power supply which works with all of the Advanced Research Instruments preamplifiers. It serves as a clean source of power. It is connected to the ARI preamplifiers via any ARI style or extension 9 pin D-Sub cables. This supply can power up to two of any ARI Corp. Amplifiers.

### SPECIFICATIONS

Output	Dual $\pm 15$ VDC/.25A
Noise	< 100 $\mu$ V rms
Power Requirements	115/220 VAC, 1/4A ( <i>Specify</i> )
Size	7"W 2.25"H 3.25"D
Weight	2 lb
Domestic Price	\$210.00

The connectors on the P-15D supply have the following pin outs:

<u>Pin</u>	<u>Description</u>
1	N/U
2	N/U
3	+15 VDC
4	N/U
5	N/U
6	Signal Ground
7	Power Ground
8	-15 VDC
9	N/U

Advanced Research Instruments  
11950 Spruce Canyon Circle  
PO Box 7427  
Golden CO 80403

[Http://www.aricorp.com](http://www.aricorp.com) [aricorp@aricorp.com](mailto:aricorp@aricorp.com)